

HLCJL-01

Headlight Wiring Diagram and Installation Guide

Passenger side white with green wire from fender harness

Driver side white with green wire from fender harness

Driver side white with yellow wire from fender harness

Driver side white with orange wire from turn signal harness

Provided wire harness

Halo wire (open wire)

Halo wire (open wire)

1. Remove Jeep grill. Once removed, remove factory headlights with the 3 bolts and plug on the backside.
2. Plug in main plug on each light, and let light loosely hang.
3. For amber halos, connect bare wire to white with green wire coming from fender wiring loom on each side.
4. Connect each halo light to provided harness, and wire after the fuse to both white with yellow wire on large plug, and white with orange for best results (halo will be on during the day as DLR and at night with headlights).
5. If you do not want to wire to both, wire after fuse to only white with yellow wire for halos to come on during the day only.

